



Device Configuration

Issue date: 03/2021
V1.0

Important User Information

Disclaimer

The information in this document is for informational purposes only. Please inform HMS Industrial Networks of any inaccuracies or omissions found in this document.

HMS Industrial Networks disclaims any responsibility or liability for any errors that may appear in this document. HMS Industrial Networks reserves the right to modify its products in line with its policy of continuous product development. The information in this document shall therefore not be construed as a commitment on the part of HMS Industrial Networks and is subject to change without notice. HMS Industrial Networks makes no commitment to update or keep current the information in this document.

The data, examples and illustrations found in this document are included for illustrative purposes and are only intended to help improve understanding of the functionality and handling of the product. In view of the wide range of possible applications of the product, and because of the many variables and requirements associated with any particular implementation, HMS Industrial Networks cannot assume responsibility or liability for actual use based on the data, examples or illustrations included in this document nor for any damages incurred during installation of the product. Those responsible for the use of the product must acquire sufficient knowledge in order to ensure that the product is used correctly in their specific application and that the application meets all performance and safety requirements including any applicable laws, regulations, codes and standards. Further, HMS Industrial Networks will under no circumstances assume liability or responsibility for any problems that may arise as a result from the use of undocumented features or functional side effects found outside the documented scope of the product. The effects caused by any direct or indirect use of such aspects of the product are undefined and may include e.g. compatibility issues and stability issues.

INDEX

1. Description.....	4
1.1 Introduction	4
1.2 About this document	4
1.3 What is needed	4
2. Airconwithme Button.....	6
2.1 Reset Wi-Fi settings.....	6
2.2 WPS mode.....	7
2.3 Change Wi-Fi channel	8
3. Configuration	9
3.3 Automatic.....	12
3.4 Manual	14
3.5 WPS.....	16
3.6 Settings	18
4. LED status information	20
4.1 LED status during Wi-Fi configuration	20
4.2 LED status during working mode.....	20

1. Description

1.1 Introduction

Airconwithme is the perfect IoT solution for AC management. It has been developed under Mitsubishi Heavy specifications and offers the possibility to control the domestic AC unit from an app available for Android and iOS.

The Airconwithme system offers functionalities like energy saving making the product the best professional solution for offices, stores, schools, or any other commercial building.




Figure 1.1 Airconwithme integration.

1.2 About this document

This document describes how to configure the Airconwithme device. It contains the meaning of the feedback light from Airconwithme LED during the configuration process and working mode.

1.3 What is needed

To use the Airconwithme system, at least, the following is needed:

- **Airconwithme device.**
Before starting to use Airconwithme, it is necessary to acquire (if the user hasn't done yet) an Airconwithme device¹. In addition, it is necessary to be close to it (See [Figure 1.2](#)).

¹ Airconwithme devices can be purchased in your usual air conditioner or heat pump reseller center.




Figure 1.2 Get close to the device.

- **Make sure Airconwithme device is compatible with the Indoor unit.**
Check [the compatibility](#).
- **Internet access².**
The Airconwithme device must be connected to internet using Wi-Fi, therefore make sure the Wi-Fi signal reaches the device location (See [Figure 1.3](#)).




Figure 1.3 Check Wi-Fi Signal.

- **Device with Internet access:**
A device with internet access is needed (Smartphone or Tablet).

Make sure the smartphone or tablet used is Android or iOS compatible.

In addition, double check that the data is turned off and Wi-Fi is turned on.

² Costs related with Internet access are not included in the Airconwithme price. Ask your Internet Service Provider about the associated costs of your Internet connection.

2. Airconwithme Button

Airconwithme devices have one unique button (See [Figure 2.1](#)).




Figure 2.1 Airconwithme's button

2.1 Reset Wi-Fi settings

To reset the Wi-Fi information in an Airconwithme device is needed to hold the button for 10 seconds (See [Figure 2.2](#)), the light of the LED will blink in green after some seconds it will turn steady green (See [Figure 2.3](#)).




Figure 2.2 Reset Wi-Fi procedure.




Figure 2.3 Reset LED feedback.

2.2 WPS mode

Press one time the button to activate the WPS mode in the Airconwithme device (See [Figure 2.4](#)), the light of the LED will blink in blue (See [Figure 2.5](#)).




Figure 2.4 WPS mode.




Figure 2.5 WPS mode LED feedback.

2.3 Change Wi-Fi channel

Holding the button for 2 seconds to change the channel of the Wi-Fi network (See [Figure 2.6](#)), the light of the LED will blink in green and it will turn steady green (See [Figure 2.7](#)). The process can be repeated until reach the channel wanted.




Figure 2.6 Change Wi-Fi channel procedure.




Figure 2.7 Change Wi-Fi channel LED feedback.

3. Configuration



Note: Make sure to reset the Wi-Fi configuration. Further information can be found in [Section 2.1](#).

There are 2 ways to realize the procedure

1. Tap on the white square in the main page (See [Figure 3.1](#)).
2. Login, tapping on settings and on the white square (See [Figure 3.2](#)).



Figure 3.1 Access to Configuration network device without login.




Figure 3.2 Access to Configuration network device from settings login.

Go to Wi-Fi settings of your mobile or Table and select the network generated by Airconwithme device (See [Figure 3.3](#)). Tap on **Next**.

In case the user is not connected to the device network a pop-up window will be shown asking to connect to it. (See [Figure 3.4](#)).

The mode to configure the Wi-Fi network can be selected as preference. Further information about each mode configurations will be found at [Section 3.3](#), [Section 3.4](#) and [Section 3.5](#).



Figure 3.3 Configuration network procedure.




Figure 3.4 Configuration network warning pop-up window.

If the configuration network has been carried out successfully the light of the LED will follow a light sequence (See [Figure 3.5](#)). Tap on **Done**.



Figure 3.5 LED configuration network sequence.

3.3 Automatic

1. Tap on **Automatic** (See [Figure 3.6](#))




Figure 3.6 Automatic configuration procedure.

2. Tap on name of the network wanted (See [Figure 3.7](#))




Figure 3.7 Wi-Fi Network selection.

3. Enter the password of the Wi-Fi network selected, to double check if the password entered is the correct one and tap on show password (See [Figure 3.8](#)). Tap on **Connect**.



Figure 3.8 Enter password.

If the configuration network has been carried out successfully the light of the LED will follow a light sequence (See [Figure 3.5](#)). To continue tap on done.

In case the light of the LED does not follow the sequence or start lighting different, start the process from the beginning.

3.4 Manual

Tap on **Manual** (See [Figure 3.9](#))




Figure 3.9 Manual configuration procedure.

- In case to select the security open, type the SSID of the Wi-Fi network wanted. (See [Figure 3.10](#)). Tap on **Connect**.




Figure 3.10 Security Open.

If the configuration network has been carried out successfully the light of the LED will follow a light sequence (See [Figure 3.5](#)). Tap on **Done**.

In case the light of the LED does not follow the sequence or start lighting different, start the process from the beginning.

- In case to select the security WEP/WAP2 type the SSID of the Wi-Fi network wanted. Also, type the password Wi-Fi network and to make sure is well entered slide Show password selector (See [Figure 3.11](#)). Tap on **Connect**.




Figure 3.11 Security WEP/ WPA2.

If the configuration network has been carried out successfully the light of the LED will follow a light sequence (See [Figure 3.5](#)). Tap on **Done**.

In case the light of the LED does not follow the sequence or start lighting different, start the process from the beginning.

In manual mode is an option for advanced configuration. (See [Figure 3.10](#) and [Figure 3.11](#)). By default, it comes in option DHCP (See [Figure 3.12](#)). Tap on **Save**.



Figure 3.12 Advanced options (DHCP).

- In case to select Static IP, type the IP address, Subnet Mask and Getaway. (See [Figure 3.13](#)). Tap on **Save**.



Figure 3.13 Advanced options (Static IP).

3.5 WPS

There are 2 ways to start the WPS configuration procedure

1. Tap on **WPS** (See [Figure 3.14](#)).
2. Press one time the button to activate the WPS. Further information can be found at [Section 2.2](#)




Figure 3.14 WPS configuration procedure.

Follow the instructions in the screen shown (See [Figure 3.15](#)). Tap on **Next**.




Figure 3.15 Instructions to perform WPS mode configuration.

the light of the LED will blink blue, 2 minutes after the WPS button of the router had been pressed the light of the LED will be off (See [Figure 3.16](#)).




Figure 3.16 Performing WPS configuration LED feedback.

If the configuration network has been carried out successfully the light of the LED will follow a light sequence (See [Figure 3.5](#)). To continue tap on **Done**.

In case the light of the LED blinks Magenta (See [Figure 3.17](#)), start the process from the beginning.




Figure 3.17 Unsuccessful connection LED feedback.

3.6 Settings

In settings the domain region where the Airconwithme device will work can be changed, also, if the installation has more than device and the user needs to identify which device is going to be configured it can be called.

Tap on **Settings** (See [Figure 3.18](#))




Figure 3.18 Settings configuration site.

- To identify to which network Airconwithme device is connected the mobile or tablet tap on Identify (See [Figure 3.19](#)). the light of the LED will blink white for 6 seconds, then it will be off (See [Figure 3.20](#)).




Figure 3.19 Settings Airconwithme.




Figure 3.20 Identify LED feedback.

- To change of Region, tap on the region wanted (See [Figure 3.19](#)). A pop-up will be shown telling that if the region is changed the configuration process must be started from the beginning (See [Figure 3.21](#)). Tap on **OK**. Tap on **Save** (See [Figure 3.19](#)).

The light of the LED will blink green for 6 seconds, then it will turn steady green (See [Figure 3.22](#))




Figure 3.21 Change region.




Figure 3.22 Selecting region LED feedback.

4. LED status information

Airconwithme device has an external LED which uses to give the user a feedback to communicate the status of the device.

4.1 LED status during Wi-Fi configuration

LED Color (s)	Behavior	Description
Blue	Blinking	Performing WPS connection (up to 2 min)
Magenta	Blink	WPS connection error
White	Blinking	Identifying Airconwithme Device
Green	Steady	Not configured
Green	Blinking	Checking device configuration parameter values (up to 2 min)
Red	Blinking	Connecting to access point and server (up to 2 min)
Yellow	Blinking	Downloading configuration. Wait (up to 2 min)
Red - Green	Alternate blinking	Error Connecting to Access point or router. Try to connect again and make sure you write the correct password.
Yellow - Green	Alternate blinking	Server not reached. Check if there is Internet connectivity on your Access Point or router.

4.2 LED status during working mode

LED Color	Behavior	Description
Off		Airconwithme device not powered or Airconwithme device working, and the AC unit is Off.
Blue	Steady	Indoor Unit ON working in Cool or Dry mode
Red		Indoor Unit ON working in Heat mode
Green		Indoor Unit ON working in Fan mode
Yellow		Indoor Unit ON working in Auto mode
Cyan		Indoor Unit working in anti-frost mode
Blue	3 blinks	Command received or sent during Cool or Dry mode
Red		Command received or sent during Heat mode
Green		Command received or sent during Fan mode
Yellow		Command received or sent during Auto mode
Cyan		Command sent during anti-frost mode
Red	Blinking	Airconwithme device trying to connect to the Internet